

Quick Guide for Hard-Wire Keypads ET268 / ET270

Terminal Wiring

12 V	Red	(+) 12Vdc power to the keypad
GND	Black	(-) Negative power to the keypad
NO	Blue	Door Strike relay N/O (normally open)
COM	Purple	Door Strike reply COM (Earth on Board)

Programming the Keypad

1. Press * (Star key)
2. Press 9999
3. Press # within 5 seconds
4. Press 1
Enter any 6 numbers for your new password
Press #
Press 001
Press #
5. Press * to save password
6. Enter your new password then press # - Finished.

